



BRX Programmable Option Modules (POM)

BX-P-ECOMLT \$69.00

The Ethernet LT POM can be connected to the Do-more! Designer programming software or HMI's that support the Do-more! protocol. This POM functions only as a server device.

| Pin # | Signal |
|-------|----------------------|
| 1 | TXD+ Transmit Data |
| 2 | TXD- Transmit Data |
| 3 | RXD+ Receive Data |
| 4 | N/C |
| 5 | N/C |
| 6 | RXD- Request to Send |
| 7 | N/C |
| 8 | N/C |




BX-P-ECOMLT Specifications

| | |
|---|---|
| Description | Standard transformer isolated Ethernet port with built-in surge protection. |
| Transfer Rate | 1 Mbps throughput max |
| Port Status LED | LINK LED is solid when network is established. ACT LED flashes when port is active. |
| Supported Protocols | Do-more! Protocol (Server) |
| Cable Recommendation | C5E-STxxx-xx from AutomationDirect.com |
| Port Type | RJ45, Category 5, Auto Crossover |
| Ethernet Port Numbers: Do-more! Protocol | 28784, UDP |
| Hot Swappable | Yes |


BX-P-USB-B \$27.00

The USB POM can only be connected to the Do-more! Designer programming software.

| Pin # | Signal |
|-------|--------|
| 1 | +5 |
| 2 | -Data |
| 3 | +Data |
| 4 | GND |



Mating face of USB type B female



BX-P-USB-B Specifications

| | |
|---------------------------|--|
| Description | USB Type B Port for programming. |
| USB Specification Version | USB 2.0 |
| Port Status LED | LED flashes when port is active |
| Cable Recommendation | USB-CBL-ABxx from AutomationDirect.com |
| Hot Swappable | Yes |